Main switch, P3, 63 A, surface mounting, 3 pole + N, 1 N/O, 1 N/C, Emergency switching off function, With red rotary handle and yellow locking ring, Lockable in the 0 (Off) position



Part no. P3-63/I4/SVB/N/HI11

207350

EL Number 1417168

(Norway)

(Norway)	
General specifications	
Product name	Eaton Moeller® series P3 Main switch
Part no.	P3-63/I4/SVB/N/HI11
EAN	4015082073503
Product Length/Depth	139 millimetre
Product height	240 millimetre
Product width	160 millimetre
Product weight	1.282 kilogram
Compliances	CE Marked
Certifications	IEC 60947 EN 60947-3 UL 508 CSA Std. C22.2 No. 14-05 VDE CSA CSA-C22.2 No. 94 CSA-C22.2 No. 60947-4-1-14 IEC/EN 60947-3 IEC/EN 60947 UL File No.: 266332 UL 60947-4-1 UL CE IEC/EN 60204 VDE 0660 CSA Class No.: 3211-05 UL Category Control No.: NLRV CSA File No.: 012528
Product Tradename	P3
Product Type	Main switch
Product Sub Type	None
Catalog Notes	Rated Short-time Withstand Current (Icw) for a time of 1 second
Features & Functions	
Features	Version as emergency stop installation Version as maintenance-/service switch Version as main switch
Fitted with:	Red rotary handle and yellow locking ring
Functions	Emergency switching off function Interlockable
Locking facility	Lockable in the 0 (Off) position
Number of poles	4
General information	
Degree of protection	NEMA 12
Degree of protection (front side)	IP65
Lifespan, mechanical	100,000 Operations
Mounting method	Surface mounting
Mounting position	As required
Operating frequency	1200 Operations/h
Overvoltage category	III
Pollution degree	3
Rated impulse withstand voltage (Uimp)	6000 V AC
Safe isolation	440 V AC, Between the contacts, According to EN 61140
Safety parameter (EN ISO 13849-1)	B10d values as per EN ISO 13849-1, table C.1
Shock resistance	15 g, Mechanical, According to IEC/EN 60068-2-27, Half-sinusoidal shock 20 ms
Suitable for	Ground mounting

	Branch circuits, suitable as motor disconnect, (UL/CSA)
Climatic environmental conditions	
Ambient operating temperature - min	-25 °C
Ambient operating temperature - max	40 °C
Ambient operating temperature (enclosed) - min	-25 °C
Ambient operating temperature (enclosed) - max	40 °C
Climatic proofing	Damp heat, constant, to IEC 60068-2-78 Damp heat, cyclic, to IEC 60068-2-30
Terminal capacities	
Terminal capacity	$1 \times (1.5 - 25) \text{ mm}^2$, flexible with ferrules to DIN 46228 $2 \times (2.5 - 10) \text{ mm}^2$, solid or stranded $1 \times (2.5 - 35) \text{ mm}^2$, solid or stranded $2 \times (1.5 - 6) \text{ mm}^2$, flexible with ferrules to DIN 46228 $14 - 2 \text{ AWG}$, solid or flexible with ferrule
Screw size	M5, Terminal screw
Tightening torque	3 Nm, Screw terminals 26.5 lb-in, Screw terminals
Electrical rating	
Rated breaking capacity at 220/230 V (cos phi to IEC 60947-3)	640 A
Rated breaking capacity at 400/415 V (cos phi to IEC 60947-3)	600 A
Rated breaking capacity at 500 V (cos phi to IEC 60947-3)	590 A
Rated breaking capacity at 660/690 V (cos phi to IEC 60947-3)	340 A
Rated operational current (Ie) at AC-3, 220 V, 230 V, 240 V	51 A
Rated operational current (Ie) at AC-3, 380 V, 400 V, 415 V	55 A
Rated operational current (Ie) at AC-3, 500 V	44 A
Rated operational current (Ie) at AC-3, 660 V, 690 V	22.1 A
Rated operational current (le) at AC-21, 440 V	63 A
Rated operational current (Ie) at AC-23A, 230 V	63 A
Rated operational current (Ie) at AC-23A, 400 V, 415 V	63 A
Rated operational current (Ie) at AC-23A, 500 V	63 A
Rated operational current (Ie) at AC-23A, 690 V	63 A
Rated operational current (Ie) at DC-1, load-break switches $I/r = 1 \text{ ms}$	63 A
Rated operational current (Ie) at DC-23A, 24 V	50 A
Rated operational current (Ie) at DC-23A, 48 V	50 A
Rated operational current (Ie) at DC-23A, 60 V	50 A
Rated operational current (Ie) at DC-23A, 120 V	25 A
Rated operational power at AC-3, 380/400 V, 50 Hz	30 kW
Rated operational power at AC-3, 415 V, 50 Hz	30 kW
Rated operational power at AC-3, 500 V, 50 Hz	30 kW
Rated operational power at AC-3, 690 V, 50 Hz	30 kW
Rated operational power at AC-23A, 220/230 V, 50 Hz	18.5 kW
Rated operational power at AC-23A, 400 V, 50 Hz	30 kW
Rated operational power at AC-23A, 500 V, 50 Hz	45 kW
Rated operational power at AC-23A, 690 V, 50 Hz	55 kW
Rated operational voltage (Ue) at AC - max	690 V
Rated uninterrupted current (Iu)	63 A
Uninterrupted current	Rated uninterrupted current lu is specified for max. cross-section.
Short-circuit rating	
Rated conditional short-circuit current (Iq)	4 kA (Load side) 100 kA (Supply side)
Rated short-time withstand current (Icw)	1.26 kA
Short-circuit current rating (basic rating)	10 kA, SCCR (UL/CSA) 150A, max. Fuse, SCCR (UL/CSA)
Short-circuit protection rating	80 A gG/gL, Fuse, Contacts
Switching capacity	
Load rating	$2 \times I\#$ (with intermittent operation class 12, 25 % duty factor) 1.3 x I# (with intermittent operation class 12, 60 % duty factor) 1.6 x I# (with intermittent operation class 12, 40 % duty factor)
Number of contacts in series at DC-23A, 24 V	1

Switching capacity (auxiliary contacts, general use) Switching capacity (auxiliary contacts, pilot duty) A600 (UL, Rated making capacity up to 690 V (cos phi to IEC/EN 60947-3) Voltage per contact pair in series 60 V Motor rating Assigned motor power at 115/120 V, 60 Hz, 1-phase Assigned motor power at 200/208 V, 60 Hz, 1-phase Assigned motor power at 200/208 V, 60 Hz, 3-phase Assigned motor power at 230/240 V, 60 Hz, 1-phase Assigned motor power at 230/240 V, 60 Hz, 3-phase Assigned motor power at 230/240 V, 60 Hz, 3-phase Assigned motor power at 460/480 V, 60 Hz, 3-phase Assigned motor power at 4575/600 V, 60 Hz, 3-phase Contacts	
Number of contacts in series at DC-23A, 120 V Switching capacity (main contacts, general use) Switching capacity (auxiliary contacts, general use) Switching capacity (auxiliary contacts, pilot duty) Rated making capacity up to 690 V (cos phi to IEC/EN 60947-3) Voltage per contact pair in series 60 V Motor rating Assigned motor power at 115/120 V, 60 Hz, 1-phase Assigned motor power at 200/208 V, 60 Hz, 1-phase Assigned motor power at 200/208 V, 60 Hz, 1-phase Assigned motor power at 230/240 V, 60 Hz, 1-phase Assigned motor power at 230/240 V, 60 Hz, 3-phase 15 HP Assigned motor power at 230/240 V, 60 Hz, 3-phase Assigned motor power at 460/480 V, 60 Hz, 3-phase Control circuit reliability Number of auxiliary contacts (change-over contacts) Number of auxiliary contacts (normally open contacts) Number of auxiliary contacts (normally open contacts) Actuator	(UL/CSA) L/CSA) L/CSA)
Switching capacity (main contacts, general use) Switching capacity (auxiliary contacts, general use) 10A, IU, (Switching capacity (auxiliary contacts, pilot duty) Rated making capacity up to 690 V (cos phi to IEC/EN 60947-3) Voltage per contact pair in series Motor rating Assigned motor power at 115/120 V, 60 Hz, 1-phase Assigned motor power at 200/208 V, 60 Hz, 1-phase Assigned motor power at 200/208 V, 60 Hz, 3-phase Assigned motor power at 230/240 V, 60 Hz, 1-phase 15 HP Assigned motor power at 230/240 V, 60 Hz, 3-phase Assigned motor power at 460/480 V, 60 Hz, 3-phase Assigned motor power at 450/480 V, 60 Hz, 3-phase Contacts Control circuit reliability Number of auxiliary contacts (change-over contacts) Number of auxiliary contacts (normally open contacts) Number of auxiliary contacts (normally open contacts) 1 Actuator	(UL/CSA) L/CSA) L/CSA)
Switching capacity (auxiliary contacts, general use) Switching capacity (auxiliary contacts, pilot duty) Rated making capacity up to 690 V (cos phi to IEC/EN 60947-3) Voltage per contact pair in series 60 V Motor rating Assigned motor power at 115/120 V, 60 Hz, 1-phase Assigned motor power at 200/208 V, 60 Hz, 1-phase Assigned motor power at 200/208 V, 60 Hz, 3-phase Assigned motor power at 230/240 V, 60 Hz, 3-phase Assigned motor power at 230/240 V, 60 Hz, 3-phase Assigned motor power at 460/480 V, 60 Hz, 3-phase Assigned motor power at 575/600 V, 60 Hz, 3-phase Contacts Control circuit reliability Number of auxiliary contacts (change-over contacts) Number of auxiliary contacts (normally open contacts) 1 Actuator	(UL/CSA) L/CSA) L/CSA)
Switching capacity (auxiliary contacts, pilot duty) A600 (UL) Rated making capacity up to 690 V (cos phi to IEC/EN 60947-3) Voltage per contact pair in series 60 V Motor rating Assigned motor power at 115/120 V, 60 Hz, 1-phase Assigned motor power at 200/208 V, 60 Hz, 1-phase Assigned motor power at 200/208 V, 60 Hz, 3-phase Assigned motor power at 230/240 V, 60 Hz, 3-phase Assigned motor power at 230/240 V, 60 Hz, 3-phase Assigned motor power at 460/480 V, 60 Hz, 3-phase Assigned motor power at 575/600 V, 60 Hz, 3-phase Contacts Control circuit reliability 1 failure mA) Number of auxiliary contacts (change-over contacts) Number of auxiliary contacts (normally open contacts) 1 Actuator	L/CSA) L/CSA)
Voltage per contact pair in series Motor rating Assigned motor power at 115/120 V, 60 Hz, 1-phase 3 HP Assigned motor power at 200/208 V, 60 Hz, 1-phase 7.5 HP Assigned motor power at 200/208 V, 60 Hz, 3-phase 15 HP Assigned motor power at 230/240 V, 60 Hz, 3-phase 10 HP Assigned motor power at 230/240 V, 60 Hz, 3-phase 15 HP Assigned motor power at 460/480 V, 60 Hz, 3-phase 40 HP Assigned motor power at 575/600 V, 60 Hz, 3-phase 50 HP Contacts Control circuit reliability 1 failure mA) Number of auxiliary contacts (change-over contacts) 0 Number of auxiliary contacts (normally closed contacts) 1 Actuator	e per 100,000 switching operations statistically determined, at 24 V DC, 10
Motor rating Assigned motor power at 115/120 V, 60 Hz, 1-phase 3 HP Assigned motor power at 200/208 V, 60 Hz, 1-phase 7.5 HP Assigned motor power at 200/208 V, 60 Hz, 3-phase 15 HP Assigned motor power at 230/240 V, 60 Hz, 1-phase 10 HP Assigned motor power at 230/240 V, 60 Hz, 3-phase 15 HP Assigned motor power at 460/480 V, 60 Hz, 3-phase 40 HP Assigned motor power at 575/600 V, 60 Hz, 3-phase 50 HP Contacts Control circuit reliability 1 failure mA) Number of auxiliary contacts (change-over contacts) 0 Number of auxiliary contacts (normally closed contacts) 1 Number of auxiliary contacts (normally open contacts) 1 Actuator	e per 100,000 switching operations statistically determined, at 24 V DC, 10
Assigned motor power at 115/120 V, 60 Hz, 1-phase 7.5 HP Assigned motor power at 200/208 V, 60 Hz, 1-phase 7.5 HP Assigned motor power at 200/208 V, 60 Hz, 3-phase 15 HP Assigned motor power at 230/240 V, 60 Hz, 1-phase 10 HP Assigned motor power at 230/240 V, 60 Hz, 3-phase 15 HP Assigned motor power at 460/480 V, 60 Hz, 3-phase 40 HP Assigned motor power at 575/600 V, 60 Hz, 3-phase 50 HP Contacts Control circuit reliability 1 failure mA) Number of auxiliary contacts (change-over contacts) 0 Number of auxiliary contacts (normally closed contacts) 1 Number of auxiliary contacts (normally open contacts) 1 Actuator	e per 100,000 switching operations statistically determined, at 24 V DC, 10
Assigned motor power at 200/208 V, 60 Hz, 1-phase 7.5 HP Assigned motor power at 200/208 V, 60 Hz, 3-phase 15 HP Assigned motor power at 230/240 V, 60 Hz, 1-phase 10 HP Assigned motor power at 230/240 V, 60 Hz, 3-phase 15 HP Assigned motor power at 460/480 V, 60 Hz, 3-phase 40 HP Assigned motor power at 575/600 V, 60 Hz, 3-phase 50 HP Contacts Control circuit reliability 1 failure mA) Number of auxiliary contacts (change-over contacts) 0 Number of auxiliary contacts (normally closed contacts) 1 Number of auxiliary contacts (normally open contacts) 1 Actuator	e per 100,000 switching operations statistically determined, at 24 V DC, 10
Assigned motor power at 200/208 V, 60 Hz, 3-phase 15 HP Assigned motor power at 230/240 V, 60 Hz, 1-phase 10 HP Assigned motor power at 230/240 V, 60 Hz, 3-phase 15 HP Assigned motor power at 460/480 V, 60 Hz, 3-phase 40 HP Assigned motor power at 575/600 V, 60 Hz, 3-phase 50 HP Contacts Control circuit reliability 1 failure mA) Number of auxiliary contacts (change-over contacts) 0 Number of auxiliary contacts (normally closed contacts) 1 Actuator	e per 100,000 switching operations statistically determined, at 24 V DC, 10
Assigned motor power at 200/208 V, 60 Hz, 3-phase 15 HP Assigned motor power at 230/240 V, 60 Hz, 1-phase 10 HP Assigned motor power at 230/240 V, 60 Hz, 3-phase 15 HP Assigned motor power at 460/480 V, 60 Hz, 3-phase 40 HP Assigned motor power at 575/600 V, 60 Hz, 3-phase 50 HP Contacts Control circuit reliability 1 failure mA) Number of auxiliary contacts (change-over contacts) 0 Number of auxiliary contacts (normally closed contacts) 1 Actuator	e per 100,000 switching operations statistically determined, at 24 V DC, 10
Assigned motor power at 230/240 V, 60 Hz, 3-phase Assigned motor power at 460/480 V, 60 Hz, 3-phase Assigned motor power at 575/600 V, 60 Hz, 3-phase Contacts Control circuit reliability 1 failure mA) Number of auxiliary contacts (change-over contacts) Number of auxiliary contacts (normally closed contacts) Number of auxiliary contacts (normally open contacts) 1 Actuator	per 100,000 switching operations statistically determined, at 24 V DC, 10
Assigned motor power at 230/240 V, 60 Hz, 3-phase Assigned motor power at 460/480 V, 60 Hz, 3-phase Assigned motor power at 575/600 V, 60 Hz, 3-phase Contacts Control circuit reliability 1 failure mA) Number of auxiliary contacts (change-over contacts) Number of auxiliary contacts (normally closed contacts) Number of auxiliary contacts (normally open contacts) 1 Actuator	e per 100,000 switching operations statistically determined, at 24 V DC, 10
Assigned motor power at 460/480 V, 60 Hz, 3-phase 40 HP Assigned motor power at 575/600 V, 60 Hz, 3-phase 50 HP Contacts Control circuit reliability 1 failure mA) Number of auxiliary contacts (change-over contacts) 0 Number of auxiliary contacts (normally closed contacts) 1 Number of auxiliary contacts (normally open contacts) 1 Actuator	per 100,000 switching operations statistically determined, at 24 V DC, 10
Assigned motor power at 575/600 V, 60 Hz, 3-phase Contacts Control circuit reliability 1 failure mA) Number of auxiliary contacts (change-over contacts) Number of auxiliary contacts (normally closed contacts) Number of auxiliary contacts (normally open contacts) 1 Actuator	per 100,000 switching operations statistically determined, at 24 V DC, 10
Control circuit reliability Control circuit reliability Number of auxiliary contacts (change-over contacts) Number of auxiliary contacts (normally closed contacts) Number of auxiliary contacts (normally open contacts) 1 Actuator	per 100,000 switching operations statistically determined, at 24 V DC, 10
Control circuit reliability 1 failure mA) Number of auxiliary contacts (change-over contacts) 0 Number of auxiliary contacts (normally closed contacts) 1 Number of auxiliary contacts (normally open contacts) 1 Actuator	per 100,000 switching operations statistically determined, at 24 V DC, 10
Number of auxiliary contacts (change-over contacts) Number of auxiliary contacts (normally closed contacts) Number of auxiliary contacts (normally open contacts) 1 Actuator	, por 100,000 systeming operations statistically determined, at 24 v DG, 10
Number of auxiliary contacts (normally closed contacts) 1 Number of auxiliary contacts (normally open contacts) 1 Actuator	
Number of auxiliary contacts (normally open contacts) 1 Actuator	
Actuator	
Actuator color Red	
Actuator type Door cou	upling rotary drive
Design verification	
Equipment heat dissipation, current-dependent Pvid 4.5 W	
Heat dissipation capacity Pdiss 0 W	
Heat dissipation per pole, current-dependent Pvid 4.5 W	
Rated operational current for specified heat dissipation (In) 63 A	
Static heat dissipation, non-current-dependent Pvs 0 W	
	he product standard's requirements.
	he product standard's requirements.
·	he product standard's requirements.
·	he product standard's requirements.
·	stance only in connection with protective shield.
	or apply, since the entire switchgear needs to be evaluated.
-	ot apply, since the entire switchgear needs to be evaluated.
	he product standard's requirements.
·	of apply, since the entire switchgear needs to be evaluated.
	he product standard's requirements.
, -	of apply, since the entire switchgear needs to be evaluated.
	or apply, since the entire switchgear needs to be evaluated.

·	anel builder's responsibility. anel builder's responsibility.
	anel builder's responsibility.
	anel builder's responsibility.
	anel builder's responsibility.
provide h	nel builder is responsible for the temperature rise calculation. Eaton will heat dissipation data for the devices.
observed	
observed	anel builder's responsibility. The specifications for the switchgear must be ed.
10.13 Mechanical function The devi	

Technical data ETIM 8.0

Low-voltage industrial components (EG000017) / Switch disconnector (EC000216)

Electric engineering, automation, process control engineering / Low-voltage switch technology / Off-load switch, circuit breaker, control switch / Switch disconnector (ecl@ss10.0.1-27-37-14-03 [AKF060013])

[AKI 000010]/		
Version as main switch		Yes
Version as maintenance-/service switch		Yes
Version as safety switch		No
Version as emergency stop installation		Yes
Version as reversing switch		No
Number of switches		1
Max. rated operation voltage Ue AC	٧	690
Rated operating voltage	٧	690 - 690
Rated permanent current lu	Α	63
Rated permanent current at AC-23, 400 V	Α	63
Rated permanent current at AC-21, 400 V	Α	63
Rated operation power at AC-3, 400 V	kW	30
Rated short-time withstand current lcw	kA	1.26
Rated operation power at AC-23, 400 V	kW	30
Switching power at 400 V	kW	30
Conditioned rated short-circuit current Iq	kA	100
Number of poles		4
Number of auxiliary contacts as normally closed contact		1
Number of auxiliary contacts as normally open contact		1
Number of auxiliary contacts as change-over contact		0
Motor drive optional		No
Motor drive integrated		No
Voltage release optional		No
Device construction		Complete device in housing
Suitable for floor mounting		Yes
Suitable for front mounting 4-hole		No
Suitable for front mounting centre		No
Suitable for distribution board installation		No
Suitable for intermediate mounting		No
Colour control element		Red
Type of control element		Door coupling rotary drive
Interlockable		Yes
Type of electrical connection of main circuit		Screw connection
Degree of protection (IP), front side		IP65
Degree of protection (NEMA)		12